


ELECTRICAL BOX BRACKET TO STUD C23, C4, C6


Features


- Replaces H-Brackets with improved design
- Thicker steel to significantly increase rigidity and help prevent box movement and trim out issues
- Works with both standard and adjustable single and double gang mud rings
- Mounts plaster rings for low voltage applications
- Additional bend points on C4 and C6 brackets for greater versatility














Part Number	Stud Wall Depth	Box Size	Depth D	Height H	Width W	Thickness T
C23	2 1/2", 3 5/8"	4", 4 11/16"	3.51"	5"	5 3/4"	0.028"
C4	2 1/2", 3 5/8", 4"	4", 4 11/16"	3.89"	5"	5 3/4"	0.028"
C6	2 1/2", 3 5/8", 5 1/2", 6"	4", 4 11/16"	5.89"	5"	5 3/4"	0.028"

UL, UR, cUL, cUR, cULus and cURus are registered certification marks of UL LLC.



Pentair products shall be installed and used only as indicated in Pentair's product instruction sheets and training materials. Instruction sheets are available at www.erico.pentair.com and from your Pentair customer service representative. Improper installation, misuse, misapplication or other failure to completely follow Pentair's instructions and warnings may cause product malfunction, property damage, serious bodily injury and/or death, and void your warranty.

© 2016 Pentair All Rights Reserved
Pentair, CADDY, CADWELD, CRITEC, ERICO, ERIFLEX, ERITECH and LENTON are owned by Pentair or its global affiliates. All other trademarks are the property of their respective owners. Pentair reserves the right to change specifications without prior notice.