


- 1) Turn off power.
 - 2) Remove glass diffuser by sliding the glass out of fixture. Remove housing cover by rotating locks.
 - 3) Hold fixture housing in desired mounting position and mark position of keyholes. Put fixture housing down and start screws at marks.
 - 4) Remove the knockout which allows for the easiest access to conduit. Assemble conduit connector, 1/2" trade size (customer supplied), to knocked out hole on fixture housing. (Reference conduit connector manufacturers instruction.)
 - 5) Run wire through assembled conduit connector.
 - 6) Slip large portion of keyhole over screwheads and push fixture to one side. This will allow both hands freedom for tightening screws.
 - 7) Tighten screws on conduit connector to clamp conduit in position.
 - 8) Make grounding connections using supplied wire nut.
 - 9) • Electrical shock, overheating, low or no light output and shortened lamp life can result if proper grounding is not done.
 - To accomplish proper grounding there must be a wire or bare metal contact between this fixture and either a grounded incoming wire or grounded metal base.,
 - When non-metallic conduit systems are used the ground wire from the fixture must terminate at the ground of the power supply panel.
- | Connect Black OR
Red Supply Wire to: | Connect
White Supply Wire to: |
|--|--|
| Black | White |
| *Parallel cord (round & smooth) | *Parallel cord (square & ridged) |
| Clear, Brown, Gold or Black
without tracer | Clear, Brown, Gold or Black
with tracer |
| Insulated wire (other than green)
with copper conductor | Insulated wire (other than green)
with silver conductor |
- *Note: When parallel wires (SPTI & SPTII) are used, The neutral wire is square shaped or ridged and the other wire will be round in shape or smooth (see illus.)*
- 
- Neutral Wire
- 10) Make wire connections (connectors provided).
 - 11) Replace housing cover and secure in place by rotating locks against the base of the housing cover.
 - 12) Insert recommended bulbs, if removed.
 - 13) Re-install glass diffuser. **CAUTION: Do not light fixture without glass diffuser in place.**
 - 14) Turn on power.