


## NL-410 / NL-411

### Adjustable Stepped Baffle with Ring

#### TRIM DIMENSIONS



Trim OD: 5"  
Aperture: 3-1/2"  
Height: 1-7/8"

#### FEATURES

##### Trim

Precision spun 0.040 aluminum baffle with deep grooves to reduce aperture glare. Non-reflective painted finishes. Gimbal ring allows lamp to be mounted on top of the trim and adjustable up to 35°. Separate trim ring available in plastic or metal, may also be used with custom combination of ring finishes.

##### Mounting

Trim includes three trim clips that securely mount trim in housing.

##### Compatible Housings

Compatible with Line Voltage and Low Voltage housings.  
See individual specification sheets for more information.

##### Lamp

###### Line Voltage

50W 120V MR16 GU10 Max. (NSL-401AT/10; NSLIC-401AT/10; NSLR-404AT/10)

###### Low Voltage

20W-75W 12V MR16 (NL-401 Series; NL-402 Series; NLIC-401 Series; NLIC-402 Series; NLR-403 Series; NLR-404 Series; NLR-405 Series)

##### Labels and Listings

cULus Listed for Damp Location when used with compatible housing.

#### IMPORTANT:

DO NOT USE GLASS LENS WHEN ALREADY USING LAMP w/ GLASS COVER

### Adjustable Stepped Baffle with Ring

- NL-410: White Adjustable Stepped Baffle with White Metal Ring
- NL-410BZ: Bronze Adjustable Stepped Baffle with Bronze Metal Ring
- NL-410CO: Copper Adjustable Stepped Baffle with Copper Metal Ring
- NL-410N: Natural Metal Adjustable Stepped Baffle with Natural Metal Ring
- NL-410P: White Phenolic Adjustable Stepped Baffle with White Plastic Ring
- NL-411: Black Adjustable Stepped Baffle with White Metal Ring
- NL-411B: Black Adjustable Stepped Baffle with Black Metal Ring
- NL-411BZ: Black Adjustable Stepped Baffle with Bronze Metal Ring
- NL-411C: Black Adjustable Stepped Baffle with Chrome Metal Ring
- NL-411CO: Black Adjustable Stepped Baffle with Copper Metal Ring
- NL-411G: Black Adjustable Stepped Baffle with Gold Metal Ring
- NL-411N: Black Adjustable Stepped Baffle with Natural Metal Ring
- NL-411P: Black Phenolic Adjustable Stepped Baffle with White Plastic Ring

# NORALIGHTING.

Type

Project

Catalog No.

Lamp/Wattage

#### Compatible Housings

##### LINE VOLTAGE

Item Number	Installation Type	Lamp	Dimensions
NSL-401AT/10	Non-IC Air-Tight New Const.	50W MR16	W: 5-5/8" L: 8-1/2" H: 5-3/4"
NSLIC-401AT/10	IC Air-Tight New Construction	50W MR16	W: 8" L: 12-5/8" H: 8"
NSLR-404AT/10	Non-IC Air-Tight Remodel	50W MR16	W: 4-1/4" L: 11-1/4" H: 5-5/8"

##### LOW VOLTAGE

NL-401QAT/20	Non-IC AT New Const., Mag.	20W MR16	W: 6" L: 9" H: 5-1/2"
NL-401QAT/37	Non-IC AT New Const., Mag.	37W MR16	W: 6" L: 9" H: 5-1/2"
NL-401QAT	Non-IC AT New Const., Mag.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401/50/277AT	Non-IC AT New Const., Mag.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401AT/1EL	Non-IC AT New Const., Elec.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401AT/2EL	Non-IC AT New Const., Elec.	50W MR16	W: 6" L: 9" H: 5-1/2"
NL-401/75	Non-IC AT New Const., Mag.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-401/75/277	Non-IC AT New Const., Mag.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-401/75/1EL	Non-IC AT New Const., Elec.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-401/75/2EL	Non-IC AT New Const., Elec.	75W MR16	W: 7" L: 11-1/2" H: 6-3/8"
NL-402S/20	Non-IC Shallow New Con., Mag.	20W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NL-402S/37	Non-IC Shallow New Con., Mag.	37W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NL-402S	Non-IC Shallow New Con., Mag.	50W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NL-402S/1EL	Non-IC Shallow New Con., Elec.	50W MR16	W: 6" L: 8-1/2" H: 3-1/2"
NLIC-401QSAT/20	IC Air-Tight New Const., Mag.	20W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401QSAT/37	IC Air-Tight New Const., Mag.	37W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401QSAT	IC Air-Tight New Const., Mag.	50W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401AT/277V	IC Air-Tight New Const., Mag.	50W MR16	W: 10-3/4" L: 17-3/4" H: 7-1/2"
NLIC-401AT/1EL	IC Air-Tight New Const., Elec.	50W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-401AT/2EL	IC Air-Tight New Const., Elec.	50W MR16	W: 7-3/4" L: 12-1/2" H: 7-1/4"
NLIC-402QSAT/20	IC Air-Tight Shallow NC, Mag.	20W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLIC-402QSAT/37	IC Air-Tight Shallow NC, Mag.	37W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLIC-402QSAT	IC Air-Tight Shallow NC, Mag.	50W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLIC-402AT/1EL	IC Air-Tight Shallow NC, Elec.	50W MR16	W: 13-1/8" L: 14" H: 5-3/8"
NLR-403S/20	Non-IC Shallow Remodel, Mag.	20W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-403S/37	Non-IC Shallow Remodel, Mag.	37W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-403S	Non-IC Shallow Remodel, Mag.	50W MR16	W: 4-7/8" L: 13-1/2" H: 3-1/2"
NLR-403S/1EL	Non-IC Shallow Remodel, Elec.	50W MR16	W: 4-7/8" L: 11-3/4" H: 3-1/2"
NLR-404QAT/20	Non-IC Air-Tight Remodel, Mag.	20W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404QAT/37	Non-IC Air-Tight Remodel, Mag.	37W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404QAT	Non-IC Air-Tight Remodel, Mag.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404/50/277	Non-IC Air-Tight Remodel, Mag.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404AT/1EL	Non-IC Air-Tight Remodel, Elec.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404AT/2EL	Non-IC Air-Tight Remodel, Elec.	50W MR16	W: 4-7/8" L: 14-1/2" H: 5-5/8"
NLR-404/75	Non-IC Remodel, Magnetic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-404/75/277	Non-IC Remodel, Magnetic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-404/75/1EL	Non-IC Remodel, Electronic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-404/75/2EL	Non-IC Remodel, Electronic	75W MR16	W: 4-7/8" L: 14-1/2" H: 6-3/8"
NLR-405AT/20	Non-IC Air-Tight Remodel	20W MR16	W: 4-3/4" L: 4-3/4" H: 4-1/4"
NLR-405AT/37	Non-IC Air-Tight Remodel	37W MR16	W: 4-3/4" L: 4-3/4" H: 4-1/4"
NLR-405AT	Non-IC Air-Tight Remodel	50W MR16	W: 4-3/4" L: 4-3/4" H: 4-1/4"

# NORALIGHTING.

6505 Gayhart St., Commerce, CA 90040  
www.noralighting.com • Specifications subject to change without notice. © 2011  
Phone: 800.686.6672 • FAX: 800.500.9955 • e-mail: nora@noralighting.com