



PASSIVE INFRARED DUAL RELAY WALL SWITCH OCCUPANCY SENSOR

PW-302 | [Wattstopper](#)

FEATURES & BENEFITS

The PW-302 Passive Infrared (PIR) Wall Switch Sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

- High sensitivity and dense coverage for exceptional performance
- Two relays for control of two separate lighting loads or circuits
- Defaults to Manual-ON to 50% operation for maximum energy savings
- Optional neutral connection with break off tab to expose neutral terminals
- 120/277VAC and 347VAC models
- Allows multi-way control from one of up to four control location

SPECIFICATIONS

GENERAL INFO

Typical Applications: Small Office, Small Conference Room, Lunch/Break Rooms

Special Features: Multi-way Dual Relay

TECHNICAL INFORMATION

IR Range On Axis: 525 SqFt

LightOutput 1FCD: Auto-ON to 50%

Load: 0-800 W 1/6 hp, 0-1000 W 1/6 hp, 0-1200 W 1/6 hp

Response Time: 5 to 30 minutes

Volts: 120/27VAC, 50/60Hz, 347VAC 650/0Hz