



GE
Lighting

35519 - GE LED Bright Stik™

LED6LS3/850

- ☞ GE's LED Bright Stik™ illuminates spaces instantly.
- ☞ Replaces 40-100 watt incandescent, halogen, and CFL
- ☞ User longer life, lower energy alternative to CFL - Last longer than CFL (15,000hrs)
- ☞ For example, using only 10 watts of energy, saves over \$82 in energy costs over the rated life of a lamp versus a standard 60-watt incandescent lamp based on \$0.11 per kWh.
- ☞ These lamps are energy efficient, contain no lead or mercury, and are compliant with material restriction requirements of RoHS.
- ☞ Worry-free use and disposal

Product Photo



GENERAL CHARACTERISTICS

Base Description	Medium Screw
Base Type	Screw-In
Dimmable	No
Primary Application	General Purpose
Product Color	White
Product Technology	LED
Rated Life (Hours)	15000 h
Dimmable / Non-Dimmable	No
Lamp Count	3
Life in Years	13.7 yr
Replacement Watts	40 W
Requested Structure	Carton
Estimated Energy Cost per Year	0.72
Base	E26
Bulb Shape	A19

PHOTOMETRIC CHARACTERISTICS

Lumens per Watt (Efficacy)	75 lm
Nominal Initial Lumen per Watt	75
Initial Lumens-nominal	450 lm
Color Rendering Index-CRI	80
Color Temperature	5000 K

PRODUCT INFORMATION

Product Code	35519
Description	LED6LS3/850
Alternative Unit Of Measure	CASE
Standard Package Quantity	16
Ean UPC	043168355193
Standard Package GTIN	10043168355190
No Of Items Per Sales Unit	
No Of Items Per Standard Package	16
Sales Unit	Case
UCC	043168355193
Alternative Unit Of Measure	EACH
Standard Package Quantity	16
Ean UPC	043168355193
Standard Package GTIN	00043168355193
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	16
Sales Unit	Each
UCC	043168355193

DIMENSIONS

Bulb Max Overall Length-MOL	4.45 mm
-----------------------------	---------

ELECTRICAL CHARACTERISTICS

Voltage <Nom>	120 V
Input Voltage [nom]	120 V
Rated power (Watts)	6 W

CAUTIONS & WARNINGS

Warning

Risk of Electric Shock

Suitable for damp locations

Not for use in totally enclosed luminaires

Not intended for use with emergency exit fixtures, emergency exit lights, electronic timers, photocells or dimmers