#### **CHOOSING THE CORRECT QUICKNET**

Select the QuickNet floor heating mat that is no larger than the heated area. The heated area is the area of the floor that does not include permanent fixtures such as cabinets, toilets, sinks or tubs. The selected mat can be configured on the jobsite to fit the shape of the area to be heated.

### For example:

If your bathroom is 9 ft X 1	0 ft =	90 sq ft
minus the cabinet area minus the toilet space minus the linen area minus the shower space	- - -	10 sq ft 6 sq ft 8 sq ft 15 sq ft
Total area to be heated	=	51 sq ft*

#### Solution:

Choose the 50 sq ft QUICKNET (QuickNet-050-1)
\*If the shower area is to be heated, select a 15 sq ft
QuickNet Extension Kit (QUICKNET-015X-1) also.

Extension kits are available to accommodate larger heated areas. Unlike standard kits, extension kits do not include the QuickStat-TC thermostat or floor sensor. The maximum installation area is 140 ft $^2$  at 120 V and 280 ft $^2$  at 240 V.


### STRAIGHTFORWARD INSTALLATION




	QuickNet	Heated area	Mat dimensions*	Power
	Catalog number	ricuted area	output	
	120 V QuickNet Stand	dard Kit (with ther	120 V	
	QUICKNET-010-1	10 sq ft	20 in x 6.2 ft	120 W
	QUICKNET-015-1	15 sq ft	20 in x 9.2 ft	180 W
	QUICKNET-020-1	20 sq ft	20 in x 12.1 ft	240 W
	QUICKNET-025-1	25 sq ft	20 in x 15.1 ft	300 W
	QUICKNET-030-1	ET-030-1 30 sq ft 20 in x 18.4 ft		360 W
	QUICKNET-035-1	35-1 35 sq ft 20 in x 21.3 ft		420 W
	QUICKNET-040-1	40 sq ft 20 in x 24.3 ft		480 W
	QUICKNET-045-1	ET-045-1 45 sq ft 20 in x 27.5 ft		540 W
	QUICKNET-050-1	KNET-050-1 50 sq ft 20 in x 30.5 ft		600 W
	QUICKNET-060-1	NET-060-1 60 sq ft 20 in x 36.4 ft		720 W
	QUICKNET-070-1	70 sq ft	20 in x 42.7 ft	840 W
	QUICKNET-080-1	ICKNET-080-1 80 sq ft 20 in x 48.9 ft		960 W
	QUICKNET-090-1	90 sq ft	20 in x 55.0 ft	1080 W
	QUICKNET-100-1	100 sq ft	20 in x 61.0 ft	1200 W
120 V QuickNet Extension Kit (without thermostat)				120 V
	QUICKNET-010X-1	10 sq ft	20 in x 6.2 ft	120 W
	QUICKNET-015X-1	15 sq ft	20 in x 9.2 ft	180 W
	QUICKNET-020X-1	20 sq ft	20 in x 12.1 ft	240 W
	QUICKNET-025X-1	25 sq ft	20 in x 15.1 ft	300 W
	QUICKNET-030X-1	30 sq ft	20 in x 18.4 ft	360 W
	QUICKNET-035X-1	35 sq ft	20 in x 21.3 ft	420 W
	QUICKNET-040X-1	T-040X-1 40 sq ft 20 in x 24.3 ft		480 W
	QUICKNET-045X-1	45 sq ft	20 in x 27.5 ft	540 W
	QUICKNET-050X-1	50 sq ft	20 in x 30.5 ft	600 W
	QUICKNET-060X-1	JICKNET-060X-1 60 sq ft 20 in x 36.4 ft		720 W
	QUICKNET-070X-1	70 sq ft	20 in x 42.7 ft	840 W
	QUICKNET-080X-1	80 sq ft	20 in x 48.9 ft	960 W
	QUICKNET-090X-1	90 sq ft	20 in x 55.0 ft	1080 W
	QUICKNET-100X-1	100 sq ft	20 in x 61.0 ft	1200 W
	240 V QuickNet Stand	dard Kit** (with thermostat)		240 V
	QUICKNET-050-2	50 sq ft	20 in x 30.5 ft	600 W
	QUICKNET-060-2	60 sq ft	20 in x 36.4 ft	720 W
	QUICKNET-080-2	80 sq ft	20 in x 48.9 ft	960 W
	QUICKNET-100-2	100 sq ft 20 in x 61.0 ft		1200 W
	240 V Extension Kit*	** (without thermostat)		240 V
	QUICKNET-050X-2			600 W
	QUICKNET-060X-2	60 sq ft	20 in x 36.4 ft	720 W
	QUICKNET-080X-2	80 sq ft	20 in x 48.9 ft	960 W
	QUICKNET-100X-2	100 sq ft	20 in x 61.0 ft	1200 W

<sup>\*</sup>Mat can be customized to fit the shape of the area to be heated.

# **TYPICAL TILE INSTALLATION**



# TYPICAL LAMINATE AND ENGINEERED WOOD INSTALLATION



# \* PENTAIR

#### NORTH AMERICA

Tel: +1.800.545.6258
Fax: +1.800.527.5703
Tel: +1.650.216.1526
Fax: +1.650.474.7711
thermal.info@pentair.com

#### ASIA PACIFIC

Tel: +86.21.2412.1688 Fax: +86.21.5426.2917 cn.thermal.info@pentair.com

# WWW.PENTAIRTHERMAL.COM

#### **EUROPE, MIDDLE EAST, AFRICA**

Tel: +32.16.213.511 Fax: +32.16.213.603 thermal.info@pentair.com

#### LATIN AMERICA

Tel: +1.713.868.4800 Fax: +1.713.868.2333 thermal.info@pentair.com

Pentair, QuickNet and QuickStat-TC are owned by Pentair or its global affiliates. All other trademarks are the property of their respective owners. Pentair reserves the right to change specifications without prior notice.

© 2005-2014 Pentair.

#### THERMAL BUILDING SOLUTIONS

EN-RaychemQuickNetfloorheating-SB-H57702 09/14



PENTAIR

<sup>\*\*240</sup> V kits are compatible with 208 V power output.





# QUICKSTAT-TC

# Programmable thermostat for increased comfort and flexibility

The QuickStat-TC thermostat includes built-in GFCI protection. The thermostat is fully programmable and automatically switches the system on to ensure a comfortable floor temperature. The QuickNet floor heating system can maintain floor temperatures up to 85°F (30°C) or more.

# **15-YEAR LIMITED WARRANTY**

The QuickNet system standard limited warranty is two years from the date of purchase. You have the option to extend the limited warranty period to 15 years for the QuickNet mat only. For more information, visit:




www.raychemfloorheating.com



# **ADVANTAGES**

# **QUICKNET FACTS**

- Ideal for new construction and for remodels only 3/16 inch (3 mm) thick
- Customizable to fit any room
- Fast installation
- No measurable electromagnetic fields (EMF)
- Maintenance-free floor heating solution
- Available in 120 V, and 208 V / 240 V



#### FREE DESIGN SERVICE

To save time on your next project, send us a sketch of your room(s) to be heated. Include the basic measurements as well as the location of your thermostat and any permanent fixtures. We will send you a detailed drawing showing you which mat(s) to buy and how to lay it out for the best coverage.

For the free design service, fax to: 650-474-7657 or email: ptm-quicknetdesign@pentair.com