







DF10P



SF10P

Decorator & Slide Dimmers

Product description

Single pole & 3-Way 1200W @ 120V/AC 1600W @ 277V/AC 0-10VDC with integrated ON/OFF switch

Design features

- Preset feature allows user to return to previous light level when turning lights ON
- Integrated full-slide control for easy, precise operation
- Can be wired as single-pole or 3-Way
- Neutral is not required for installation of device
- Adjustable high-level trim setting for optimal lamp compatibility
- Decorator dimmers have removable faceplates to allow for color changes and each package includes three colors
- Color change kits (DF10P only)
- Compatible with dimmable LED and Fluorescent 0-10V ballasts
- Compatible with any decorator wallplate or screwless decorator wallplate

Decorator dimmers () us 426


		Compatible	Rating		
Catalog No.	Description	Lamp Types	Watt	V/AC	Color Suffix
□ DF10P	Decorator dimmer Single pole/3-Way preset	0-10VDC LED/FLR	1200 1600	120 277	C1, C2, C4, C5
□ DCK1	Color change faceplate for DF10P	_	-	-	A, B, BK, GY, LA,V, W

Slide dimmers (U) us 426

		Compatible	Kating		
Catalog No.	Description	Lamp Types	Watt	V/AC	Color Suffix
☐ SF10P	Slide dimmer Single pole/ 3-Way preset	0-10VDC LED/FLR	1200 1600	120 277	A, B, BK, GY, LA, V, W

Color ordering information

For ordering devices, include Catalog no. followed by the color suffix: A (Almond), B (Brown), BK (Black), GY (Gray), LA (Light Almond), V (Ivory), W (White), C1 (Color Change Kit: A, W, V), C2 (Color Change Kit: LA, W, V), C4 (Color Change Kit: BK, W, V), C5 (Color Change Kit: BK, W, GY),



Compliances, specifications and availability are subject to change without notice.







OS10D7

Occupancy & Vacancy Dimmer Sensor

Product description

Single pole & 3-Way 10A @ 120V/AC 8A @ 277V/AC 0-10VDC **FLR** and **LED** ballasts

Design features

- 3 in 1 device combining dimming, switching and motion sensing
- Digital PIR sensor for occupancy (Auto ON/Auto OFF) and vacancy (Manual ON/Auto OFF) sensing
- Provides 180 degree field of view and 1000 sq. ft. of major motion coverage
- Full-range Preset dimming control provided with horizontal dim/bright bar
- · Green LED indicates motion detection
- Selectable ambient light override in occupancy sensor models
- Selectable time delay of 15 seconds (Test mode, changes to 2 minutes after 2 minutes of powering up), 5 minutes (factory default), 15 minutes and 20 minutes
- Occupancy Sensor version can be toggled between Auto ON/Auto OFF or Manual ON/ Auto OFF
- Vacancy sensor meets California Title 20 (VS10D7 only)
- Compatible with any decorator wallplate or screwless decorator wallplate
- Neutral required for installation of device
- · California Title 20 compliant

Occupancy & vacancy dimmer sensor (1) us 476

	- 1.0	Compatible	Compatible Rating			
Catalog No.	Description	Lamp Types	Watt	V/AC	Color Suffix	
□ OS10D7	Occupancy sensor & dimmer with LED Single pole/3-Way preset	0-10VDC LED/FLR	1200 2200		BK, GY, LA, V, W	
□VS10D7	Vacancy sensor & dimmer with LED Single pole/3-Way preset	0-10VDC LED/FLR	1200 2200	120 277	BK, GY, LA, V, W	

Color ordering information

For ordering devices, include Catalog no. followed by the color suffix: BK (Black), GY (Gray), LA (Light Almond), V (Ivory), W (White)



Compliances, specifications and availability are subject to change without notice.

Electrical Sector 203 Cooper Circle Peachtree City, GA 30269 United States Eaton.com Eaton.com/arrowhart Electrical Sector Canada Operations 5925 McLaughlin Road Mississauga, Ontario, L5R 1B8 Canada EatonCanada.ca Electrical Sector
Mexico Operations
Carr. Tialnepantla Cuautitlán Km 17.8 s/n
Col. Villa Jardín esq.
Cerrada 8 de Mayo
Cuautitlán, Mexico CP 54800
México
Eaton.mx
Eaton.com/arrowhart

Eaton.com/arrowhart Cuautitlán, Mexico Eaton.mx

Eaton is a registered trademark.

Powerina Business Worldwide

1000 Eaton Boulevard Cleveland, OH 44122 United States Eaton.com © 2017 Eaton All Rights Reserved Printed in USA Publication No. SA620011EN March 2017

All other trademarks are property of their respective owners.