



Powering Business Worldwide

pe.eaton.com

CH 3/4-inch loadcenter

CH16L125B

UPC: 782113097473

Dimensions: 16.75 IN * 14.31 IN * 3.88 IN (L * W * H)

Notes: Suitable for use as service equipment when not more than six service disconnecting mains are provided or when not used as a lighting and appliance panelboard.

Warranty: Limited lifetime

Specifications:

- **Type:** Main lug only
- **Amperage Rating:** 125A
- **Box Size:** B
- **Bus Material:** Copper
- **Cover:** Ch8bf-combination, ch8bs-surface
- **Enclosure:** NEMA 1
- **Enclosure Material:** Metallic
- **Feed Type:** Overhead or underground
- **Main Circuit Breaker:** CH
- **Number Of Circuits:** 16
- **Number Of Wires:** Three-wire
- **Phase:** Single-phase
- **Wire Size:** #6-2/0

Supporting documents:

- [Type CH Circuit Breakers and Loadcenters](#)
- [Eatons Volume 1-Residential and Light Commercial](#)
- [Cutler-Hammer Type CH and BR Loadcenters - Instructions](#)
- [Eaton Specification Sheet - CH16L125B](#)

Certifications: No Data

Product compliance: No Data



