
NTS-5023 Front Loading Fresnel Lens with Specular Clear Reflector and Trim

DIMENSIONS



FEATURES

Trim

Precision spun 0.050 aluminum high grade specular clear reflector with high grade fresnel lens attached to trim. Easy lift and turn lens removal for re-lamping. Reflector includes two socket positions for optimum light control and output.

Note: Shallow housings must use lowest socket position.

Mounting

Trim includes two "V" torsion springs to mount trim securely to housing. Replacement "V" torsion springs are available (NRA-86).

Compatible Housings

Compatible with Line Voltage housings.

See individual specification sheets for more information.

Lamp

Line Voltage

25W A19 Maximum (NHIC-501QAT; NHRIC-504QAT)

35W PAR30 Maximum (NHIC-501QAT; NHIC-527QAT; NHRIC-504QAT; NHRIC-527QAT) 60W A19 Maximum (NH-501Q; NHR-504Q)

Labels and Listings

cULus Listed for Wet Location when used with Compatible Housings



Type


Project

Catalog No.


Lamp/Wattage

HOUSING DIMENSIONS


NH-501Q / NHIC-501QAT




NHIC-527QAT



NHR-504Q / NHRIC-504QAT



NHRIC-527QAT



Front Loading Fresnel Lens w/Specular Clear Reflector and Trim

NTS-5023W: Front Loading Fresnel Lens with Specular Clear Reflector and White Trim

Compatible Housings

LINE VOLTAGE			
Item Number	Installation Type	Lamp	Dimensions
NH-501Q	Non-IC New Construction	60W A19	W: 7-1/4" L: 10-1/2" H: 7-1/2"
NHIC-501QAT	IC Air-Tight New Construction	35W or 25W	W: 7-1/4" L: 10-1/2" H: 7-1/2"
NHIC-527QAT	Shallow IC AT New Const.	35W PAR30	W: 7" L: 10-1/2" H: 5-7/8"
NHR-504Q	Non-IC Remodel Housing	60W A19	W: 5-1/2" L: 13-1/2" H: 7-1/2"
NHRIC-504QAT	IC Air-Tight Remodel Housing	35W or 25W	W: 5-1/2" L: 13-1/2" H: 7-1/2"
NHRIC-527QAT	Shallow IC AT Remodel	35W PAR30	W: 6-3/4" L: 13-1/4" H: 5-1/2"