



Powering Business Worldwide

pe.eaton.com

CH 3/4-inch loadcenter

CH2L125SP

UPC: 782114190470

Dimensions: 9.5 IN * 4.5 IN * 3.13 IN (L * W * H)

Notes: Ground bar kits priced separately. Suitable for use as service equipment when not more than two service disconnecting mains are provided or when not used as a lighting and appliance panelboard.

Warranty: Limited lifetime

Specifications:

- **Special Features:** Standard
- **Type:** Main lug only
- **Amperage Rating:** 125A
- **Box Size:** 6
- **Bus Material:** Copper
- **Enclosure:** NEMA 1
- **Enclosure Material:** Metallic
- **Feed Type:** Overhead or underground
- **Main Circuit Breaker:** CH
- **Mounting:** Surface
- **Number Of Circuits:** 2
- **Number Of Poles:** Four-pole
- **Number Of Wires:** Three-wire
- **Phase:** Single-phase
- **Wire Size:** #1-4/0 AWG

Supporting documents:

- [Type CH Circuit Breakers and Loadcenters](#)
- [Eaton's Volume 1-Residential and Light Commercial](#)
- [Cutler-Hammer Type CH and BR Loadcenters - Instructions](#)
- [Eaton Specification Sheet - CH2L125SP](#)

Certifications: No Data



Product compliance: No Data

© 2016 Eaton. All rights reserved.