


3800, 4200, 4300, 4800,

5400, or 7400 lumens



The Philips Day-Brite / Philips CFI FluxGrid LED recessed offers architectural appeal with "must have" features. Two different lens styles, discrete air handling, integral emergency, and access to the boards and driver from below make FluxGrid an ideal solution for a wide range of applications.

Ordering guide — Standard configurations available with all choices, unless otherwise noted.

Base configurations selections indicated by blue.

Example: 2FGG42B840-4-D-UNV-DIM

Width	Family	Ceiling Type	Air Function	Lumens	Color	Length	Center Diffuser	Voltage	Driver	Options
2	FG	G				4				
2 2'	FG FluxGrid	G Grid	Blank Static H Air return	Standard Configurations 38L 3800 nominal delivered lumens 43L 4300 nominal delivered lumens 48L 4800 nominal delivered lumens 54L 5400 nominal delivered lumens 74L 7400 nominal delivered lumens Base Configurations 42B 4200 nominal delivered lumens	830 80 CRI, 3000K 835 80 CRI, 3500K 840 80 CRI, 4000K 850 80 CRI, 5000K	4 4'	D Diffuse (ribbed) DS Diffuse (smooth)	UNV Universal voltage 120-277V 1201 120V 2771 277V 347 347V	DIM ²³ Dimming SDIM ⁴ Step dimming to 40% input power XDIM ¹ MarkX phase dimming L3D ⁵ Lutron Hi-lume A 1% dimming LDE Lutron LDE5 5% dimming DALI DALI	F1 3/8" flex, 3 wire 18 gauge 6' F2 3/8" flex, 4 wire 18 gauge 6' F1/D 3/8" twin flex, 3 wire 18 gauge 6' for dimmable luminaires F2/5W 3/8" single flex, 5 wire 18 gauge 6' for dimmable luminaires F2/6W 3/8" single flex, 6 wire 18 gauge 6' for dimmable and EMLED luminaires GLR Fusing, fast blow EMLED SWZDT' Integral sensor, daylighting and occupancy, advanced grouping with dwell time DAYOCC' Integral sensor, daylighting and occupancy, basic grouping CHIC Chicago Plenum rated

Footnotes

- 1 XDIM requires 120V or 277V specification. Not available on 30L package.
- 2 Integral SWZDT and DAYOCC options dimmable to 5% via wireless wall switch. See p. 2.
- 3 Non-controls configurations are 0-10V dimmable to 1% for standard configurations. Base configurations are 0-10V dimmable to 10%.
- 4 Consult factory for SDIM on 74L package.
- **5** Specify up to 43L package. Consult factory for higher lumen packages.
- 6 Philips Bodine BSL310, 1100lm nominal delivered
- 7 Specify DIM driver option only

Accessories (order separately)

- FMA24 2'x4' "F" mounting frame for NEMA "F" mounting
- FGD4L FG 4' ribbed replacement lens
- FGDS4L FG 4' smooth replacement lens
- FGHD4L FG 4' air return ribbed replacement lens
- FGHDS4L FG 4' air return smooth replacement lens
- FSK24 2'x4' surface mount field installation kit (factory welded seams)
- FSF24 2'x4' surface mount field assembly kit (field assembled)

Energy data

Luminaire	Catalog Number	Input Power	Efficacy
	2FGG38L840	31.8	120
	2FGG43L840	36.2	119
2x4 Standard	2FGG48L840	41.5	116
	2FGG54L840	48.9	114
	2FGG74L840	69.2	106
2x4 Base	2FGG42B840	33.9	124





3800, 4200, 4300, 4800, 5400, or 7400 lumens

Application

- 3" deep low profile configuration provides minimal penetration into the plenum space.
- Acrylic diffuser available in ribbed and smooth configurations provides even illumination with comfortable appeal.
- Standard and base configurations available in multiple lumen packages to suit the needs of various applications.
- Lambertian distribution creates uniform horizontal and vertical illuminance on the work plane and reduces scalloping on the walls.
- CRI 80 minimum color rendering with balanced spectrum.
- LEDs coupled with standard dimming provide prolonged lumen maintenance.
 Optional integral sensors contribute further to LED lumen maintenance.
- Designed for use with standard 15/16" wide Grid (NEMA "G") T-bars. Drywall or plaster applications require use with the FMA24 "F" mounting frame accessory (sold and shipped separately).
- Continuous row mounting is possible with a 1" gap between fixtures accommodated by others.

Enclosure

- Opal acrylic diffuser provides visually comfortable lumenance without compromise to luminaire efficacy.
- Diffuser requires no frames or fasteners and can be easily removed from below without the use of tools.

Construction/Finish

- Uncomplicated design is 3" deep with minimal material overlap creating several benefits:
- Less material required
- Less packaging required
- Reduced weight for ease of handling and transit
- Less energy required for construction and assembly
- More luminaires can be shipped per truck to reduce fuel consumption
- Metal side covers are die formed with a conical shape to enhance light distribution and visual aesthetic.
- Injection molded lens retainers allow for easy, tool-free access to the LED boards and driver from below, and provide positive lens retention,

- Luminaire finish is matte white polyester powder coat for high quality, durable finish.
- · T-bar grid clips are integral to the body.
- Air return option provides air flow through a unique lens retainer design. Air passes through architectural forms in the lens retainers (each end), and through the end plate of the luminaire. A cover plate is provided to control air flow through the luminaire, or make it static as required.
- Integral controls options include sensor mounted in one lens retainer. Controls are commissioned via intuitive Philips app on a Droid smartphone either through NFC or an IR blaster
- EMLED option requires the emergency battery pack be installed with a top side cover. Access from above.
- To estimate lumen output in emergency mode, multiply emergency pack wattage by efficacy, then by 1.10.

General notes

- · All options are factory installed.
- · All accessories are field installed.
- Many luminaire components, such as reflectors, refractors, lenses, sockets, lampholders, and LEDs are made from various types of plastics which can be adversely affected by airborne contaminants. If sulfur based chemicals, pertroleum based products, cleaning solutions, or other contaminants are expected in the intended area of use, consult factory for compatibility.

Electrical

- Integral sensor options for occupancy sensing and/or daylight harvesting are available for additional energy savings with no reduction of life or increase in installation labor.
- Standard configurations provide up to 120 lumens per watt and are available with 5 lumen packages and 3000, 3500, 4000, and 5000K color temperatures.
- Base configurations provide up to 124 lumens per watt and are available in 4200 lumen flux and 3500K and 4000K color temperatures.
- LED boards are accessible from below by removal of the lens. Lens removal is tool-free by compressing the sides and pushing to one end
- LED driver is accessible from below by removal of the lens and integral wireway cover. The wireway cover is easily removed with a flat head screwdriver.
- Other driver options including step dimming (SDIM, 100%/40%), DALI, phase dimming (XDIM), and Lutron are available.

- Five year limited luminaire warranty includes LED boards and driver. Visit www.philips. com/warranties for complete warranty information.
- TM-21 predicted L70 lumen maintenance up to 70,000 hours.
- cETLus listed to UL and CSA standards, suitable for damp locations.
- FluxGrid luminaires are DesignLights
 Consortium qualified. Please see the DLC
 QPL list for exact catalog numbers
 (http://www.designlights.org/QPL).

DAYOCC & SpaceWise DT (SWZDT)


- Commissioning via compatible Android phone and Philips Field App
- Dimming via compatible wireless wall switch only (see below)
- Register for the commissioning app at http:// registration.componentcloud.philips.com/ appregistration/
- Integral sensing options (DAYOCC, SWZG2, SWZDT) may not be combined
- For more information including recommended switches, refer to the following –


DAYOCC – www.lightingproducts.philips. com/documents/webdb2/DayBrite/pdf/ DAYOCC_sensor.pdf

SWZDT – www.lightingproducts.philips.com/documents/webdb2/DayBrite/pdf/SWZDT_sensor.pdf

3800, 4200, 4300, 4800, 5400, or 7400 lumens

Dimensions









Controls sensor integrated into one lens retainer.




The air return option allows air to flow through vents in the lens retainers on each end. Air blades are provided on each end of the luminaire to control air flow to the plenum.





3800, 4200, 4300, 4800, 5400, or 7400 lumens

Air return



Plenum Pressure, Inches W.G.

Return air - noise criteria

All luminaire sizes

					CF	М			
Mode		27	37	53	62	71	80	90	102
Air¹	NC (dB)	<15	24	25	29	33	35	38	40

				CFM				
Mode		31	38	45	51	61	65	74
Air+Controls ²	NC (dB)	<15	19	21	25	28	30	34

^{1.} Air-only option includes air return lens retainers and pattern control blades on both ends of luminaire.
2. Air-Controls includes the air return lens retainer and pattern control blade on one end of the luminaire.

Air+Controls includes the air return lens retainer and pattern control blade on one end of the luminaire Control lens retainer on the other with matching width.

3800, 4200, 4300, 4800, 5400, or 7400 lumens

Photometry

2x4 FluxGrid recessed LED, base configuration, 4200 nominal delivered lumens

LER - 124

 Catalog No.
 2FGG42B840-4-D-UNV-DIM

 Test No.
 36564

 S/MH
 1.2

 Lamp Type
 LED

 Lumens
 4212

 Input Watts
 34

Comparative yearly lighting energy cost per 1000 lumens – \$1.94 based on 3000 hrs. and \$.08 pwr KWH

The photometric results were obtained in the Philips Day-Brite laboratory which is NVLAP accredited by the National Institute of Standards and Technology.

Photometric values based on test performed in compliance with LM-79.

Candlepower

Angle	End	45	Cross	Back-45
0	1567	1567	1567	1567
5	1541	1556	1559	1556
15	1467	1473	1476	1473
25	1323	1330	1339	1330
35	1124	1147	1165	1147
45	896	949	978	949
55	659	737	779	737
65	404	534	587	534
75	203	323	365	323
85	43	104	108	104

Light Distribution Mean Property Degrees Lumens % Luminaire 0-30 1176 27.9 0-40 1893 44.9 0-60 3273 77.6 0-90 4215 100 0-180 4216 100

Average Luminance										
Zone End 45° Cross										
45	8102	8584	8845							
55	7349	8219	8685							
65	6120	8077	8890							
75	5025	7991	9014							
85	3186	7597	7905							

Coefficients of Utilization

EFFEC	TIVE FLC	OR CAVI	TY REFLE	CTANCE	20 PER (ofc=0.20)	
pfc =	20							
Ceil		80			70			50
Wall	70	50	30	70	50	30	50	30
RCR								
0	118	118	118	115	115	115	111	111
1	108	103	98	106	101	96	96	93
2	97	90	82	95	88	81	84	79
3	90	79	70	86	77	69	73	68
4	81	69	60	80	68	59	66	58
5	76	63	54	72	60	53	58	52
6	69	56	46	68	55	46	54	46
7	65	51	41	63	50	41	48	40
8	59	46	38	58	46	38	45	36
9	56	42	34	55	41	34	40	34
10	53	40	32	52	39	32	38	30

2x4 FluxGrid recessed LED, standard configuration, 4300 nominal delivered lumens

Catalog No. 2FGG43L840-4-D-UNV-DIM

 Test No.
 36563

 S/MH
 1.2

 Lamp Type
 LED

 Lumens
 4318

 Input Watts
 36

Comparative yearly lighting energy cost per 1000 lumens – \$2.02 based on 3000 hrs. and \$.08 pwr KWH.

The photometric results were obtained in the Philips Day-Brite laboratory which is NVLAP accredited by the National Institute of Standards and Technology.

Photometric values based on test performed in compliance with LM-79.

Candlepower

Angle	End	45	Cross	Back-45
0	1613	1613	1613	1613
5	1587	1602	1604	1602
15	1511	1517	1520	1517
25	1362	1369	1380	1369
35	1157	1182	1199	1182
45	922	978	1006	978
55	679	759	800	759
65	416	514	605	514
75	209	332	377	332
85	44	106	111	106

Light Distribution

_		
Degrees	Lumens	% Luminaire
0-30	1210	28.0
0-40	1948	45.1
0-60	3367	77.9
0-90	4320	100
0-180	4321	100

Avera	age L	umina	ance
Zone	End	45°	Cros
45	0344	0043	0000

LER - 119

	_		
Zone	End	45°	Cross
45	8341	8843	9099
55	7569	8460	8924
65	6302	7782	9152
75	5161	8208	9321
85	3259	7773	8155

Coefficients of Utilization

EFFEC	EFFECTIVE FLOOR CAVITY REFLECTANCE 20 PER (pfc=0.20)										
pfc =	20										
Ceil		80			70			50			
Wall	70	50	30	70	50	30	50	30			
RCR											
0	118	118	118	115	115	115	111	111			
1	108	103	98	106	101	96	96	93			
2	97	90	82	95	88	81	84	79			
3	90	79	70	86	78	69	75	68			
5	81	69	60	80	68	60	66	58			
5	76	63	54	73	61	53	58	52			
6	69	56	47	68	56	46	54	46			
7	65	51	42	63	51	41	48	40			
8	59	46	38	58	46	38	45	36			
9	56	42	34	55	41	34	40	34			
10	53	40	32	52	39	32	38	30			

© 2017 Philips Lighting Holding B.V. All rights reserved. Philips reserves the right to make changes in specifications and/or to discontinue any product at any time without notice or obligation and will not be liable for any consequences resulting from the use of this publication. philips.com/luminaires



Philips Lighting North America Corporation 200 Franklin Square Drive, Somerset, NJ 08873 Tel. 855-486-2216

Philips Lighting Canada Ltd. 281 Hillmount Rd, Markham, ON, Canada L6C 2S3 Tel. 800-668-9008