

ENCLOSED ELECTRONIC Transformers

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

PRODUCT DESCRIPTION

SMART Electronic Transformers, available from 60 to 300 watts, incorporate trouble-shooting diagnostics, full scale dimming and a compact size with auto reset, soft start and short circuit protection technologies.

FEATURES

- 1W minimum load
- Use for all initial installations to ensure safe and primary side connections in a wiring compartment
- Dimming with Electronic Low Voltage dimmers

SPECIFICATIONS

Construction: Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

Output: 12V, 24V

Frequency: 20khz

Details: In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

Standards: UL Listed

ORDER NUMBER

Model	Output	L	W	H
EN-1260-RB-AR	12V, 1 x 60W	6 $\frac{5}{8}$ "	1 $\frac{5}{8}$ "	1 $\frac{1}{8}$ "
EN-1275-RB-AR	12V, 1 x 75W	6 $\frac{5}{8}$ "	1 $\frac{5}{8}$ "	1 $\frac{1}{8}$ "
EN-12100-RB-AR	12V, 1 x 100W	6 $\frac{1}{4}$ "	3"	1 $\frac{3}{4}$ "
EN-12150-RB-AR	12V, 1 x 150W	6 $\frac{1}{4}$ "	3"	1 $\frac{1}{4}$ "
EN-24150-RB-AR*	24V, 1 x 150W	6 $\frac{1}{2}$ "	3"	1 $\frac{5}{8}$ "
EN-B12PY-AR*	12V, 1 x 250W	6 $\frac{1}{2}$ "	3 $\frac{3}{8}$ "	2 $\frac{1}{2}$ "
EN-B24PZ-AR*	24V, 1 x 300W	6 $\frac{1}{2}$ "	3 $\frac{3}{8}$ "	2 $\frac{1}{2}$ "

*Includes LED indicator lights and integral push-in terminals

ACCESSORIES

Multiple Terminal Block

Accommodates up to 6 output connections for 14 AWG wires. Terminal block is used to easily wire together multiple output connections for a neat under cabinet installation without the use of open splices. Perfect for wiring up to 3 button lights at 20W or 6 button lights at 10W.

Model	L	W	H
MTB-01	3 $\frac{3}{4}$ "	1 $\frac{3}{4}$ "	$\frac{7}{8}$ "

EN- - -

Example: **EN-12100-RB-AR**

waclighting.com
Phone (800) 526.2588
Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive
Port Washington, NY 11050

Central Distribution Center
1600 Distribution Ct
Lithia Springs, GA 30122

Western Distribution Center
1750 Archibald Avenue
Ontario, CA 91760