

Prepared By: **Project:** Type: Date:



Features and Benefits

FLUORESCENT REPLACEMENT - Replace conventional fluorescent T8 and T12 linear tubes

EASY TO INSTALL - Simply cut the ballast out, and rewire sockets directly to line voltage

SAVE ENERGY AND MONEY - Provides same output as fluorescent but uses far less energy

ENCLOSED FIXTURE RATED - May be used in enclosed and open

DIFFUSION COATING - Will maintain the same light quality over time and won't yellow, shrink, or wrinkle

BALLAST BYPASS - Internal driver eliminates the need for external ballasts or drivers

INSTANT ON - No warmup time required, full brightness instantly

LOW FLICKER - Less than 5% flicker

MERCURY FREE - Environmentally friendly vs fluorescent technologies

SHUNTED AND NON-SHUNTED - Works on shunted and nonshunted sockets

Technical Specifications

Product Type Linear **Bulb Shape** T8 Nominal Length 4FT Finish Frosted Wattage 14\W

Wattage Equivalency 32W Fluorescent

Typical Lumen Output 1800 Efficacy 129 lm/W 5000K Daylight Color Temperature

CRI 82 Base Type G13 50,000 hours L70 Lifespan Operating Temperature -20°C - 45°C Nο

Dimmable Beam Angle 240°

5-Year, No-Compromise Warranty Warranty Type B, Double Ended wiring Installation Type

For Use in Emergency Fixtures No For Use Outdoors in Open Fixtures No

Electrical Characteristics

Input Voltage 120-277V Power Factor 0.9 Operating Frequency 50 / 60 Hz Input Current @ 120V 102mA THDi <20%

Listings

UL Recognized Yes **UL** Classified

Meets NSF/ANSI standards for use in Food Zone (non-**NSF** Listed

contact), Splash, and Non-Food Zones

This product is on the Design Lights Consortium (DLC) **DLC** Listed

Qualified Products List and is eligible for rebates from DLC

Member Utilities.

DLC Model Number T8-14-48G-850-DE-BYP

DLC Product Code PJ5VSR8I

CEC Status Lawful for sale in California

Minimum Compartment Size

Length x Width x Height [mm]	Lamp Quantity	
47.8 x 23.8 x 3.0	4	

Case and Pallet Dimensions

	QTY	LENGTH	WIDTH	HEIGHT
CASE	25	48.8	5.9	5.9
PALLET	1200	49.2	39.4	46.1

Wiring Diagram | Line | Fluorescent Lamp | Fluores

